

	CRMX Nova FX RDM (Flex reconfigurable)	CRMX Nova TX2 RDM (RDM transmitter)	CRMX Nova RX RDM (RDM receiver)	CRMX Nova TX2 (DMX transmitter)	CRMX Nova TX (DMX transmitter)	CRMX Nova RX (DMX receiver)
Model code (Order code)	IN-RFX1 (800-3001)	IN-RTX2 (800-2101)	IN-RRX1 (800-2001)	IN-DTX2 (800-1102)	IN-DTX1 (800-1101)	IN-DRX1 (800-1001)
Supported protocols						
USITT DMX-512 (1986 & 1990) and DMX512-A	Yes	Yes	Yes	Yes	Yes	Yes
Art-Net I, II & 3, ETCNet 2 & 3, Strand ShowNet, Streaming ACN, Pathport, KiNet V1 & V2	Yes, input any protocol and output any protocol	Yes, input any protocol	No	Yes, input any protocol	No	No
RDM ANSI E1.20	Yes	Yes	Yes	No	No	No
Works with CRMX SuperNova RDM Controller	Yes	Yes	Yes	Yes, configuration only	No	No
Firmware upgrade	Ethernet	Ethernet	XLR	Ethernet	XLR	XLR
DMX interface						
Number of universes supported	1	2	1	2	1	1
Full DMX fidelity and frame integrity	Yes	Yes	Yes	Yes	Yes	Yes
Error correction and packet recovery	Yes	Yes	Yes	Yes	Yes	Yes
Frame synchronization	Less than 0.01 ms	Less than 0.01 ms	Less than 0.01 ms	Less than 0.01 ms	Less than 0.01 ms	Less than 0.01 ms
End-to-end DMX latency	Less than 5 ms	Less than 5 ms	Less than 5 ms	Less than 5 ms	Less than 5 ms	Less than 5 ms
Auto sensing of DMX frame rate and size	Yes	Yes	Yes	Yes	Yes	Yes
Supported DMX frame rates	0.8 – 7352 Hz Transmitter mode / 1 – 830 Hz ¹ Receiver mode	0.8 – 7352 Hz	1 – 830 Hz ¹	0.8 – 7352 Hz	0.8 – 7352 Hz	1 – 830 Hz ¹
Number of DMX channels supported	0 – 512	0 – 1024	0 – 512	0 – 1024	0 – 512	0 – 512
Loss of DMX input behavior	DMX output will go into high impedance state	Timeout after 1.25 s	DMX driver will go into high impedance state	Timeout after 1.25 s	Timeout after 1.25 s	DMX driver will go into high impedance state
ESD protected interfaces	Yes	Yes	Yes	Yes	Yes	Yes
W-DMX™ G2/G3/G4 Compatibility ²	Yes, in receive mode	No	Yes	No	No	Yes
Power						
High voltage input	100-240VAC / 47-70Hz / 0.12A / 10W	100-240VAC / 47-70Hz / 0.25A / 22W	100-240VAC / 47-70Hz / 0.12A / 10W	100-240VAC / 47-70Hz / 0.25A / 22W	100-240VAC / 47-70Hz / 0.12A / 10W	100-240VAC / 47-70Hz / 0.12A / 10W
Low voltage input	12VDC ±20% / 0.6A / 7.5W	12VDC ±20% / 1A / 12W	12VDC ±20% / 0.2A / 2.5W	12VDC ±20% / 1A / 12W	12VDC ±20% / 0.3A / 4W	12VDC ±20% / 0.2A / 2.5W
Power over Ethernet	Yes	Yes	No	Yes	No	No
Transient protected power inputs	Yes	Yes	Yes	Yes	Yes	Yes
RF characteristics						
Modes of operation	Transmitter, Receiver	Transmitter	Receiver	Transmitter	Transmitter	Receiver
Automated Cognitive Coexistence	Yes	Yes	Yes	Yes	Yes	Yes
Dynamic adaptive frequency hopping	Yes	Yes	Yes	Yes	Yes	Yes
Recoverable Radio Packet Error Rate	30%	30%	30%	30%	30%	30%
Operational frequency range	2402-2480 MHz	2402-2480 MHz	2402-2480 MHz	2402-2480 MHz	2402-2480 MHz	2402-2480 MHz
RF output in high power mode	300 mW (25 dBm) ³	300 mW (25 dBm) ³	300 mW (25 dBm) ³	300 mW (25 dBm) ³	300 mW (25 dBm) ³	N/A
RF output in normal power mode	100 mW (20 dBm)	100 mW (20 dBm)	100 mW (20 dBm)	100 mW (20 dBm)	100 mW (20 dBm)	N/A
RF output in low power mode	35 mW (15 dBm) or 10 mW (10 dBm)	35 mW (15 dBm) or 10 mW (10 dBm)	35 mW (15 dBm) or 10 mW (10 dBm)	35 mW (15 dBm) or 10 mW (10 dBm)	35 mW (15 dBm) or 10 mW (10 dBm)	N/A
RF modulation	GFSK	GFSK	GFSK	GFSK	GFSK	GFSK
Sensitivity at 0.1% Packet Error Rate	-96 dBm	-96 dBm	-96 dBm	-96 dBm	-96 dBm	-96 dBm
Tested link range (High power mode using standard antennas in free line-of-sight)	Up to 1000 m	Up to 1000 m	Up to 1000 m	Up to 1000 m	Up to 1000 m	Up to 1000 m
Recovery time upon loss of radio link	Less than 1 s	N/A	Less than 1 s	N/A	N/A	Less than 1 s
Approvals						
FCC: 15.247&68 Class B; Canada ICES 003 CE; EN 301 489-1; EN 301 489-3; EN 300 328; SS-EN 61547:2009; EN 60 950; SRRC - China; ARIB STD-T66 - Japan	Yes	Yes	Yes	Yes	Yes	Yes
Environment						
Operating temperature range (ambient)	-20° C to +50° C -4° F to 122° F	-20° C to +50° C -4° F to 122° F	-20° C to +50° C -4° F to 122° F	-20° C to +50° C -4° F to 122° F	-20° C to +50° C -4° F to 122° F	-20° C to +50° C -4° F to 122° F
Humidity	0-90% non-condensing	0-90% non-condensing	0-90% non-condensing	0-90% non-condensing	0-90% non-condensing	0-90% non-condensing
Physical						
Enclosure	Anodized extruded aluminum	Anodized extruded aluminum	Anodized extruded aluminum	Anodized extruded aluminum	Anodized extruded aluminum	Anodized extruded aluminum
Dimensions (W x H x D) excluding antenna	110 x 44 x 160 mm 4.3" x 1.7" x 6.3"	220 x 44 x 125 mm 8.6" x 1.7" x 4.9"	110 x 44 x 160 mm 4.3" x 1.7" x 6.3"	220 x 44 x 125 mm 8.6" x 1.7" x 4.9"	110 x 44 x 160 mm 4.3" x 1.7" x 6.3"	110 x 44 x 160 mm 4.3" x 1.7" x 6.3"
Weight	0.8 kg, 1.8 lbs	0.9 kg, 2.0 lbs	0.7 kg, 1.5 lbs	0.9 kg, 2.0 lbs	0.7 kg, 1.5 lbs	0.7 kg, 1.5 lbs
Connectors						
Antenna connector	RP-TNC female	RP-TNC female	RP-TNC female	RP-TNC female	RP-TNC female	RP-TNC female
DMX connectors	1 XLR 5-pin female	2 XLR 5-pin male	1 XLR 5-pin female	2 XLR 5-pin male	1 XLR 5-pin male	1 XLR 5-pin female
Ethernet connectors	1 RJ45	1 Neutrik® Ethercon™ RJ45		1 Neutrik® Ethercon™ RJ45		
DC input	Pluggable terminal strip, Phoenix® MSTB 2.5	Pluggable terminal strip, Phoenix® MSTB 2.5	Pluggable terminal strip, Phoenix® MSTB 2.5	Pluggable terminal strip, Phoenix® MSTB 2.5	Pluggable terminal strip, Phoenix® MSTB 2.5	Pluggable terminal strip, Phoenix® MSTB 2.5
AC input	IEC 320-C14 Male	IEC 320-C14 Male	IEC 320-C14 Male	IEC 320-C14 Male	IEC 320-C14 Male	IEC 320-C14 Male
Supplied accessories	AC power cord, DC power connector, 2 dBi RP-TNC antenna	AC power cord, DC power connector, 2 dBi RP-TNC antennas	AC power cord, DC power connector, 2 dBi RP-TNC antenna	AC power cord, DC power connector, 2 dBi RP-TNC antennas	AC power cord, DC power connector, 2 dBi RP-TNC antenna	AC power cord, DC power connector, 2 dBi RP-TNC antenna